



G Radio 2-Way Portable LTE Push to talk (PTT) Radio Manual



The powerful talk2me portable 2-way radio is our advanced radio with cellular connectivity that offers connectivity regardless of your location. With the talk2me 2-way international radio network you can stay in touch with your team or join the all-new citizens band community group for continuous unlimited radio conversations at talk2chat.com, with talk2me you are always connected.

UPC 791043586506

Page 1

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual

talk2me

2-WAY DIGITAL RADIO

Table of Contents

Introduction	Page No.
Introduction and Hardware Overview	3
Device Introduction	3
Package Contents	3
SIM Card Information	4
Power button	5
Front Display Panel	6
Functions of the radio.	7
Options menus.	8
Group menu	8
Member menu	8
Settings menu	8-11
Mine menu information	12
Optional radio features for SOS	12
Optional radio features for GPS	13
Radio functionality tips.	13
Solving guidance for problems	15-16
Technical Specifications	16
Support	17
Compliance	17
Trademarks	17
Warranty	18
FCC Declaration of Conformance	18
FCC RF Radiation Exposure Statement (SAR)	19
Safety Warnings	20
Safety and Compliance	20
Maintenance & Care	21
Legal Notices	22
Product Images	23
Replacement Parts List	24

UPC 791043586506

Page 2

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual



Introduction and Hardware Overview

This section provides a basic introduction and hardware overview:

- Device Introduction.
- Package Contents.
- SIM card information.
- Get familiar with the buttons and power on.
- Primary Front Display.
- Functions of the radio.

Device Introduction

The **talk2me G Radio Portable LTE PTT Radio** can provide VOD services (Voice over data) to almost any location utilizing cellular broadband technology.

Fast, reliable and private communications are now just a simple click of the push to talk button provides continuous connectivity for voice communications.

Package Contents

Your package contains the following items:

- **G Radio Portable LTE PTT Radio**
- 1 x Pre-Installed Nano SIM card
- 1 x Headset Microphone Cable
- 1 x USB Power Adapter
- 1 x USB-C Cable

UPC 791043586506

Page 3

talk2me 2-Way Digital Radio

Talk2me Social Inc.

847 S Randall Road Ste 400

Elgin, IL 60123

(815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual

talk2me

2-WAY DIGITAL RADIO

SIM Card Information

A SIM card WILL be preinstalled in the radio.

Do not remove the SIM card unless advised to do so by a support team member.

Overview of installing the SIM card:

To install a SIM in **the radio** the gold side faces towards front of the radio and the SIM notch faces upwards ward. (See example)

To install the SIM card:

1. Ensure that power to the radio is off.
2. Remove the attached battery/clip from the radio unit.
3. Remove the SIM cover and then open up the desired SIM slot
4. The SIM should lock into place by using your finger to lock the SIM into the slot.

This device offers dual SIM capability, however if you are using one SIM card you should always use SIM card slot #1. (Examples Below)



SIM card slot #1

UPC 791043586506

Page 4

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Power button.

Let's go over the buttons and functions that will help you get used to your new radio unit,



Now that you know your buttons we power on the radio, all other functions will be discussed later in this manual.

Power On/Off key (Red back key)

- Push in and hold the Power button for 3 seconds to turn on the radio.
- Push in and hold the Power button for 3 seconds to turn off the radio.

Once the radio has powered up you will be taken to the main display screen below:

UPC 791043586506

Page 5

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual



talk2me

2-WAY DIGITAL RADIO

Front Panel display screen.

The radio displays status information on the front panel. (From top to bottom)



1. **Antenna signal: 4G** displays current network technology, signal strength and SIM card slot in use.
2. **SOS Icon:** When SOS red icon is displayed, the SOS feature is available to be activated, see SOS features for more information.
3. **GPS Icon:** When the GPS icon is displayed it means the feature is activated, when the icon turns green it means that radio unit has GPS connectivity, see GPS features for more information.
4. **Battery Icon:** Shows current battery levels, more detailed battery information can be found in the radios settings menu.
5. **Group Icon**  indicates current group channel.
6. **Member Icon**  indicates your current member's name.
7. **Operator** indicates current carrier being used.
8. **Speaker Icon: Idle** means listening to the channel.
9. **Red Speaker Icon: Member** indicates current member speaking.
10. **Time and Date** indicates current date and time from the tower.

UPC 791043586506

Page 6

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Functions of the radio.

Let's go over the buttons that will help you get used to your new radio unit.



From the top of the radio to the bottom:

1. **PTT (Push to talk button on microphone).** – The large push to talk button is located on hand microphone and is easy to use. Just press and hold for 1 second before you start talking and then hold while transmitting your message and then release when done.
2. **Vol+/Vol-** - These buttons control the volume of the radio and also are the up and down selectors for any options.
3. **Menu** – This button allows you to display and select the available options such as settings, members and groups.
4. **OK** – This button acts as the confirm button for entry changes.
5. **OK/SOS** - This button when held down for 3 seconds will trigger the SOS activation mode, to end SOS just press the same button again.

UPC 791043586506

Page 7

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

6. **Power/Exit.** – This button allows you to exit any current menus options and also services as the radios off and on button, See Power button for details.

Options menu.

There are 4 options to choose from when pressing the menu button.

- A. Group.
- B. Member.
- C. Settings.
- D. Mine.

To choose from any of these options use the Vol+/- buttons on the side of the radio and then hit the OK button to enter the desired menu.

A. Group menu.

The following option allows you to select the desired GROUP channel you want to enter. Use the Vol+/- buttons on the side of the radio and then hit the OK button to enter the desired group.

B. Member menu.

The following option allows you to select the desired member you want to have a 1 on 1 private conversation with. Use the Vol+/- buttons on the side of the radio and then hit the OK button to select the desired member. Reminder that the member must be online to communicate with.

C. Settings menu.

The following options will help you customize your radio unit. The number below corresponds with the settings option.

UPC 791043586506

Page 8

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Available options are:

1. Display settings.
2. Volume settings.
3. Keypad Lock settings.
4. Key wakeup settings.
5. Call in wakeup settings.
6. Voice play settings.
7. Power savings settings.
8. Signal value information.
9. Double card SIM card settings.
10. Battery Information.
11. Service Information.
12. GPS Information.
13. IMEI QR Code and Information.
14. Restore factory settings.
15. APN settings.

1. Display Settings:

Available options are:

- Dormancy Settings: This allows you to set the desired radio screen alive time.
- Back Light Settings: This allows you to set the desired screen brightness.
- Language Settings: This allows you to set the desired radio language.
- Time Zone Settings: This allows you to set your current GMT time zone.

2. Volume Settings:

Available options are:

- Volume: This allows you to set the desired loudspeaker volume.
- PTT prompt tone: This allows you to turn on/off the PTT Tone.
- Keypad Tone: This allows you to turn on/off the touch key tones.
- Time Zone Settings: This allows you to set your current GMT time zone.
- Send Configuration: Allows you to increase/decrease your volume output.
- Receive Configuration: Allows you to increase/decrease your volume output.

UPC 791043586506

Page 9

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

3. Keypad Lock Settings:

This option allows you to set the radio keypad lock to avoid unwanted touches or radio option changes. Available settings are: Automatic, Manual and OFF.

Note: Holding down the menu button for 3 seconds will also activate the Keypad Lock feature, hold for 3 more second to release the lock.

4. Key Wakeup Screen Settings:

This option allows you to wake up the screen display with the touch of any key. Available settings are: ON and OFF.

5. Call in wakeup Settings:

This option allows you to wake up the screen display with any type of PTT call. Available settings are: ON and OFF.

6. Voice play Settings:

This option allows you to use the guided voice prompts for every single prompt and action. Available settings are: ON and OFF.

7. Power saving mode Settings:

Adjust the radio's power consumption settings depending on your needs. Available settings are: High efficiency, Power Saving, Superpower Saving.

8. Signal Value Information:

Displays the current radio signal value, if you are having signal issues this menu can help provide the current RSSI signal score. Score range -48~-120 dbm are acceptable for radio use.

9. Double SIM card Settings:

This setting allows you to set the priority SIM card slot. Recommended to always leave at Automatic for best performance.

UPC 791043586506

Page 10

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual



10. Battery Information:

Displays the current battery state of the radio in score value and the available talk time remaining on the radio unit.

11. Service Information:

Displays the current radio network information:

- Current Group
- My Radio user ID
- Operator for SIM Slot 1
- ICCID for SIM Slot 1
- Operator for SIM Slot 2
- ICCID for SIM Slot 2

12. GPS Information:

Displays the current GPS state of the radio. Feature must be activated by the provider to use this feature.

13. IMEI QR Code Information:

Displays the current radio IMEI number and scannable QR code.

14. Reset Factory Settings:

This setting allows you to reset the radio back to its factory state.

15. APN Settings:

Allows you to choose the APN type. Available options are: Station APN, Auto APN, and Manual APN. It is highly recommended that you do not modify this section unless your told by a trained staff member.



D. Mine menu option.

Displays the current radio IMEI number, Radio user ID and radio software version.

Optional Radio features.

In this section we will review two radio option features that available for an additional cost.

- SOS Broadcast service.
- GPS Radio tracking service.

1. SOS – Emergency Call

This feature allows the company dispatcher to know when a radio unit is experiencing an emergency that requires priority attention. Once a radio unit is subscribed to the SOS service a red icon will appear at the top of the radio display screen (see example below):





To activate the SOS Emergency, call on your radio hold down the OK button for 3 seconds and this will automatically send a signal to the company dispatcher and other radio units that the SOS is active and provide other units with location information and your Radio ID for immediate notification, all users in the group with SOS activated will receive this information. It is important that you use this option in conjunction with a company dispatcher account as only the dispatcher software can clear the SOS alert.





2. GPS Device tracking.

This feature allows the company dispatcher or mobile application users to the exact location of the radio units assigned with this feature.

- When the  GPS icon is white this will indicate that the GPS is available but unable to receive a signal from the satellite.
- When the  GPS icon is green this will indicate that the GPS is receiving a signal from the satellite.

Radio functionality tips.

Features and tips:

Poor and no signal issues:

Note: When in a weak signal environment and with poor call quality, you can choose power save mode or normal mode. The call quality will be improved, but the machine also consumes more power.

Automatic screen shutdown:

If there is no button operation within the set time, the radio will automatically shut down the screen.

Transmit prompt sound:

After enabling this function, press and release the PTT key will emit a "beep" prompt sound, which will improve the call experience. When this function is turned off, pressing the

UPC 791043586506

Page 13

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

PTT key will result in no prompt sound.

Top LED display light:

The top LED will help you to identify the current radio status.

Status	LED Indication	Time
Search Network	Green light flashing fast	
Awaiting	Green light flashing slowly	0.5S on, 3.5S off
Transmitting	Constant Red	
Receiving	Constant Green	

Using earpiece headset: (K Type)

Included with every G Radio, the K type headset provides microphone and headset listening when plugged into the K port.

Battery charge:

It is imperative to always keep your radio unit charged to avoid loss of use.

Select a group (Group call):

Press the menu button then select the group menu, press the ^v volume buttons to browse the available group:

- Press the exit key to exit the group selection status,
- **Press the OK key to confirm entry into the group.**

If you press the PTT key, you can initiate a call to the group (with a red light on), accompanied by a prompt sound and screen display.

UPC 791043586506

Page 14

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Select members to 1 on 1 chat with. (Private radio call)

Press the menu key and then select the member option to enter member selection and press the $\wedge \vee$ volume buttons to browse the available members:

- If you press the exit key, you can exit the member selection status
- **Press the OK key to confirm the selection of the member.**

Now you can press the PTT button, a private call can be made to the member (with a red light on) accompanied by a prompt sound and screen display.

Solving guidance for problems:

Phenomena	Solving guidance
Equipment unresponsive	<ul style="list-style-type: none"> • Low battery level: The battery may have been depleted, please replace the battery or charge it. • SIM card malfunction: Check or renew/replace the SIM card. • Poor battery contact: Reinstall the battery or clean the battery contact points.
Insufficient standby time	<ul style="list-style-type: none"> • Battery performance degradation: replace the battery or buy one more battery for later use.
Charging fault	<ul style="list-style-type: none"> • Battery performance degradation: replace the battery • Poor connection: Check the connect condition

UPC 791043586506

Page 15

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

	<p>or replace the charging cable</p> <ul style="list-style-type: none">• Low battery voltage: Charge for about half an hour, then unplug and recharge again• Battery malfunction: replace the battery• Charger malfunction: replace the charger
Unable to connect to the network	<ul style="list-style-type: none">• Signal too weak: Move area and retry• Not on server: Confirm that the SIM card has been installed, and the SIM card is in normal use state. Confirm the local telecom operator has a band covering the radio.

Technical and Environmental

Specifications

- Dimensions: 4.33"x2.36"x1.42"
- Weight: > 7.6 oz
- Battery Capacity: 8800 mAh, 3200 mAh actual.
- Operating temperature: -10°C to 60°C
- Audio Power Output 2W@10%
- Radio Manufacturer: **QUANZHOU WURUI ELECTRIC CO LTD.**
- Module Name: **G Radio for talk2me USA**
- Bands available for LTE: **B2, B4, B5, B7, B12, B13, B14, B17, B41, B66.**
- Carrier Aggregation supported: **NO**

Radio WIRED connectivity Interface(s):

- 1 USB-C port for charging (bottom of radio).
- 1 USB-C port for programming (left side of radio).
- 1 K Port for external handset/headset/microphone.

Radio WIRELESS connectivity Interface(s):

LTE

Radio antenna connectivity Interface(s):

Built in antenna for both LTE and GPS

UPC 791043586506

Page 16

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual



Radio mobility connectivity Interface(s):

Dual Nano SIM card slots

Radio software Interface(s):

Linux kernel

Radio Key Features: Factory unlocked device can be used with any carrier.

Support

Thank you for purchasing this talk2me product. You can visit www.talk2me.us support to obtain more information about your product, get help, access the latest downloads and manuals.

Compliance

For regulatory compliance information, visit <https://talk2me.us>

See the regulatory compliance document before connecting the power supply.

Trademarks

© talk2me®, talk2chat® and the talk2me® logo are trademarks of talk2me Social, Inc., Any non-talk2me trademarks are used for reference purposes only.

Warranty

UPC 791043586506

Page 17

talk2me 2-Way Digital Radio

Talk2me Social Inc.

847 S Randall Road Ste 400

Elgin, IL 60123

(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual



talk2me **PRODUCT LIMITED WARRANTY TERMS AND CONDITIONS**

This talk2me® branded product, as supplied and distributed by talk2me and delivered new, and is warranted by talk2me® against manufacturing defects in materials and workmanship for a limited warranty period of:

- 1) 1 year from the date of purchase.

talk2me Social Inc.
847 S Randall Road
Ste 400
Elgin, IL 60123
USA

FCC Declaration of Conformance

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

UPC 791043586506

Page 18

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

Operations in the 5.850-5.895GHz band are restricted to indoor usage only.

FCC RF Radiation Exposure Statement (SAR)

This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with a minimum distance of 35 centimeters between the radiator and your body.

Safety Warnings

Adapter

Do not use any other power adapter except the one that accompanies this unit or a power adapter identified in the list below.

Use of another adapter could result in damage to the unit.

The following power adapter is qualified for use with this talk2me® radio: (specified the adapter specifications, brand, make, type and other restrictions)

Caution

Ensure to connect the power cord of power adapter to a socket-outlet with grounding connection.

Safety and Compliance

Read before Use

UPC 791043586506

Page 19

talk2me 2-Way Digital Radio

Talk2me Social Inc.

847 S Randall Road Ste 400

Elgin, IL 60123

(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

We recommend you read the following sections thoroughly before use. talk2me Social Inc. is not liable for malfunctions or damage resulting from misuse of the modem.

Safety Precaution

Please observe the following safety precautions.

Use the chargers, cables or accessories approved by the device manufacturer.

Do NOT disassemble or modify the device. Doing so voids the warranty.

Prevent wetness from penetrating internal parts. Using the device in wet or damp environment (for instance, charging it in a wet environment like bathtub or bathroom) may result in malfunctions.

Do NOT use this device near source of heat or fire, such as oven, microwave, stove, or heater.

Keep your device away from cooking appliances.

Do NOT place the device in places with heated atmosphere (dryer, sauna, hot water).

Do NOT use the device and disconnect all cables at places with fire or explosion risks.

Avoid strong physical impact (heavy objects or excessive force).

Keep your device away from liquid or conductive materials.

Do NOT charge the device when either the device, the adapter, or the cable is wet. It may cause short-circuit.

Power off the device when near medical equipment or high-precision control systems to avoid potential interference.

Charge with specified voltage only.

Place the device on a flat, stable surface for optimal use.

Keep the device and adapter away from children and pets.

The device must be disposed of in accordance with the locally applicable environmental regulations.

Keep the device away from magnetic items such as magnetic strip cards or items that generate strong electronic or magnetic fields, such as a microwave.

Do NOT store the device in an overheated environment.

Do NOT use the device when it is overheated.

Disconnect all the the cable connections when the device is not in use.

Place the device in places with good signal strength.

UPC 791043586506

Page 20

talk2me 2-Way Digital Radio

Talk2me Social Inc.

847 S Randall Road Ste 400

Elgin, IL 60123

(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

Make sure the adapter you use with the device meets the approved standards and specifications.

Disposal and Recycling

Do not dispose of the router in a household garbage bin.

Products with this label must be taken to specific collection points at the end of their life.

You can learn more about how to recycle your mobile device by visiting the CTIA website at

www.ctia.org/news/how-to-recycle-your-mobile-device

Maintenance & Care

- Avoid extreme temperature or direct sunlight.
- Clean handset with soft, dry cloth. Do NOT use alcohol solvent (color may fade)
- The warranty does not cover malfunctions caused by misuse.
- Stop all the applications and shut down the device before cleaning it.
- Keep the device and its accessories dry at all times.
- If anomaly occurs, contact your providers support immediately.
- When storing the device, do NOT store it in a container with dampness or under extended heat.
- Avoid always dropping the device or strong physical impact.

Legal Notices

Copyright Statements

Copyright ©2024 talk2me Social Inc. All rights reserved.

No part of this document may be duplicated, reproduced, shared, or used in any form, regardless written or electronically, without the prior written consent of **talk2me Social Inc.** and its affiliates.

The product described in this document contains software developed by **talk2me Social Inc.** and licensed third parties. Unless instructed or licensed otherwise by **talk2me Social Inc.** or other affiliated entities, you must NOT (1) modify, amend, translate, reverse-engineer or derive this product; (2) reproduce

UPC 791043586506

Page 21

talk2me 2-Way Digital Radio

Talk2me Social Inc.

847 S Randall Road Ste 400

Elgin, IL 60123

(815)556-0600 – <https://talk2me.us>



Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

the software or any part of this; (3) rent, lease, transfer or re-license the software or any part of this, or transfer the rights of the software; (4) remove any statement or labeling information of the product and the software in this product; (5) tamper, change or replace the software, or any attempt to impact the integrity of the software. If any of the violation above occurs, your license in using the software will be terminated.

Trademark Statements

talk2me Social ® is a trademark of **talk2me Social Inc.**, the product names in this site, and the other trademarks, logos, and service marks (collectively the "Trademarks") used in this site are the property of **talk2me Social Inc.** or their respective owners. Nothing contained in this site should be construed as granting by implication, estoppel, or otherwise, a license or right of use of **talk2me Social** or any other Trademark displayed in the site without the prior written permission of **talk2me Social**. or its respective owner.

The Wi-Fi Logo is a certification mark of the Wi-Fi Alliance.

Changes

The functions of the product and associated peripherals or accessories are described in this document are based on the current hardware, software and/or local network conditions at the time of writing, and thus may vary due to conditions set by local network service providers or carriers. Therefore, all information described herein is subject to change without prior notice.

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>



talk2me

2-WAY DIGITAL RADIO

Product Images.



UPC 791043586506

Page 23

talk2me 2-Way Digital Radio

Talk2me Social Inc.
847 S Randall Road Ste 400
Elgin, IL 60123
(815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual

Replacement Parts List.

Part Image	Description	UPC
	Removable Belt Clip for G Radio	791043586537
	Removable Battery for G Radio	791043586520
	USB A to USB C Power Cable for talk2me Radios	791043586544
	USB A Power Block for talk2me Radios	791043586551

UPC 791043586506

Page 24

talk2me 2-Way Digital Radio

Talk2me Social Inc.
 847 S Randall Road Ste 400
 Elgin, IL 60123
 (815)556-0600 – <https://talk2me.us>







Manual can be found at <https://talk2me.us/gradiomanual.pdf>

Scan for manual

talk2me

2-WAY DIGITAL RADIO

	K Type Replacement Headpiece	791043586568
	Replacement STANDARD USA Sim card	791043586483
	Replacement ENHANCED INTERNATIONAL Sim card	791043586476
	Replacement Head unit for G Radios	791043586469

If you need a part that is not listed, please contact us.

UPC 791043586506

Page 25

talk2me 2-Way Digital Radio

Talk2me Social Inc.
 847 S Randall Road Ste 400
 Elgin, IL 60123
 (815)556-0600 – <https://talk2me.us>

Manual can be found at <https://talk2me.us/gradiomanual.pdf>



Scan for manual